



SiX™ Two-Way Wireless Keypad

Security and Home Control

Optimized for the Honeywell Home Lyric™ Controller and Lyric Gateway, the SiX Two-Way Wireless Keypad enables easy, on-premises security system control for the ultimate convenience and flexibility. Sleek and stylish, it blends with any décor and can be mounted on the wall or placed on tabletops, nightstands or virtually anywhere in the home.

Easier to Install

The small size makes the SiX Two-Way Wireless Keypad ideal for mounting in tight, hard-to-fit spaces. Installation is simple with the wall mount or optional desk mount kit.

Easier to Sell

Your customers can quickly arm and disarm their systems from any location within the home—a great option that adds value to any sale.

Users can conveniently listen to system status and see updates at a glance.



FEATURES

SIZE AND WEIGHT

Height: 4.65-inches (118-mm)

Width: 3.70-inches (94-mm)

Depth: 0.95-inches (25-mm)

Weight: 0.55-pounds (0.26-kilograms)

DISPLAY

Two-line Liquid Crystal Display

Up to 16 characters on each line

EXTERNAL BUTTONS AND I/O

CONNECTORS

Buttons:

Security

Emergency response

Input and Output: Speaker

Connectors and Modules:

Backup battery module

WIRELESS AND CELLULAR

Antennas: SiX™ Technology antenna to support Lyric wireless sensors

SOUNDS AND VOICE

Sounds: Chime alerts users to sensor status (example: a door opens or closes)

Voice Announcement: Announces system status in English (example: armed away)

EMERGENCY RESPONSE AND ALERTS

Dedicated emergency response button for users to request assistance from authorities

Emergency Response Types:

Fire

Police

Medical

Emergency Alerts:

A loud alarm or sound for:

Break-ins, when system is armed

Potentially unsafe levels of smoke or carbon monoxide

SETUP AND PROGRAMMING

Remote Programming:

Support for 100% programming and testing using AlarmNet 360™ from a smartphone, tablet or web browser

Support for scheduling and delivering software or firmware updates to Lyric keypads over-the-air

Support for remote diagnostics and troubleshooting

Local Programming:

Support for enrolling keypads into the system at the site in the absence of connection to AlarmNet 360

Support for testing installation at the site in the absence of connection to AlarmNet 360

SiX™ Two-Way Wireless Keypad

Security and Home Control

SPECIFICATIONS

POWER AND OPERATING CONDITIONS

Power:

Plug-in power supply
110VAC to 9VDC/1.0A Adapter

Backup Battery:

24-hour (600 mAh)
Rechargeable NiMH cells
rated at 7.2VDC

Operating Conditions:

32°F–122°F (0°C–50°C)

ORDERING

LKP500-EN	SiX Two-Way Wireless Keypad
LKP500-ENC	SiX Two-Way Wireless Keypad (Canada)
LKP500-DK	SiX Two-Way Wireless Keypad Desk Stand
LKP500-24B	Backup Battery for SiX Two-Way Wireless Keypad (24-hour)

For more information

security.honeywellhome.com



Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492
resideo.com

All trademarks are property
of their respective owners.

L/LRCSRTKD/D | 07/19
© 2019 Resideo Technologies, Inc.
This product is manufactured
by Resideo and its affiliates. The
Honeywell Home trademark is
used under license from Honeywell
International Inc. All rights reserved.

Honeywell Home