



Lyric™ Gateway



Simply the Fastest Install

The Lyric Gateway security and home control system from Honeywell Home serves as the central hub for controlling security, lifestyle management, lights, locks, thermostats and more and is designed for the way people really live. Combining a security system and home automation with simplicity, portability and flexibility, the Lyric Gateway is a game changer — truly plug and play and delivers a great connected home experience right out of the box.



Gateway to More Growth

- Beautifully designed app-driven interface ideal for today's consumers
- Reach new customers — including the mobile/millennial segment, renters and new home buyers
- Open ecosystem integrates with the latest third party, connected home devices — a great way to earn more RMR

Gateway to More Installations

- True plug-and-play setup with informative voice guidance that makes installation simple, walking dealers through each step of the configuration
- Auto-enrollment of encrypted SiX™ sensors saves installation time and reduces errors
- Simple, fast programming with AlarmNet 360™
- Efficiencies such as these help dealers to increase installs from two to three per day

Gateway to More Profits

- AlarmNet 360 cloud-based business management platform helps dealers proactively recommend additional solutions to drive RMR
- Ethernet connection simplifies installations and eliminates sunset issues
- Remote diagnostics and account management saves time, and user-replaceable batteries and radios reduce truck rolls
- Prevent account takeovers and reduce attrition with the Honeywell Home exclusive Lyric Lock

Lyric Gateway

FEATURES AND SPECIFICATIONS

SIZE AND WEIGHT

Height

8.82 inches (22.4cm)

Depth

1.4 inches (3.6cm)

Width

6.97 inches (17.7cm)

Weight

2.2 pounds (1 kg)

USER INTERFACE

Capacitive touch interface with advanced voice guidance.

ACCOUNT PROTECTION

Lyric Lock

SiX Two-Way Wireless devices are locked into the Lyric panel and must be unpaired by the installing dealer to be used again—protecting the accounts and hardware you've enrolled.

I/O CONNECTORS

Input and Output

- Speaker
- Microphone
- Sounder with 85 dB intensity

Connectors and Modules

- Cellular module tray (end-user replaceable)
 - Internal backup battery module (end-user replaceable)
-

BUILT-IN/SUPPORTED TECHNOLOGY

Built-in Technology

- Wi-Fi® (802.11 b/g/n); (2.4 GHz)
- Ethernet port (10/100)
- Z-Wave® Plus; Network Wide Inclusion supported
- SiX Two-Way Wireless Technology
- Honeywell Home 5800 Series wireless sensors

Supported Technology

- CDMA-1xRTT (800, 1900MHz); Plug-in Option
 - GSM-3G HSPA (850, 1900MHz); Plug-in Option
-

CELLULAR (OPTIONAL)

GSM: AT&T® and Rogers™

CDMA: Verizon®

SOUNDS AND VOICE

Sounds

10 selectable chime sounds when a sensor is tripped, allowing for different sounds for any door/window (ex: a door opens or closes)

Voice Announcement

Listen to system state, sensor state, and more (e.g., armed away or front door open)

Lyric Gateway

USERS AND TWO-WAY WIRELESS KEYS

Users
48 system users

- User Profiles**
- Installer
 - Master User
 - Standard User
 - Guest
 - Duress

Wireless Keys

- Honeywell Home SiX Two-Way Wireless and 5800 Series Wireless Keys
- Supports up to eight wireless keys, each typically assigned to one user
- Wireless key supports up to eight action keys

WIRELESS SENSORS AND KEYPADS

- Supported Devices**
- 64 wireless sensors
 - SiX Two-Way Wireless Sensors
 - 5800 Series sensors

- Common SiX Sensors**
- Sensor for doors and windows
 - Motion detector
 - Glassbreak detector

- Smoke detector with one-go-all-go capabilities
- Siren with audible and visual indications

Keypads

- Supports eight Lyric Keypads
- Arm and disarm
 - Status of system
 - Seek emergency response
 - Sounds and voice announcements

CONNECTED SOLUTIONS

Z-Wave® Support
76 Z-Wave devices

- Common Solutions**
- Six Z-Wave thermostats
 - Six door locks
 - Four Z-Wave garage doors

- 60 light modules, light dimmers, appliance modules, window shades or blinds, water valves and sirens or strobes

Wi-Fi® Thermostats

Four Lyric Wi-Fi thermostats

CONNECTED APPS

Remote Operation
Resideo Total Connect Remote Services application on iOS (iPhone® and iPad®), Android™ and Web

- Features**
- Manage users of the system
 - Create, run or delete 100 smart scenes to combine states of discrete devices into one command
 - Configure smart scenes to occur based on time, device or system trigger, or on manual activation

- Set up and receive notifications based on activity at the site

Local Control and Setup

- Support for MyHome Gateway app¹ (iOS and Android)
- Subscription-free option for users to control their system from anywhere at the premise
- Up to eight devices

¹ MyHome Gateway is a free application that may be downloaded from Apple® iTunes® or Google Play®.



Lyric Gateway

EMERGENCY RESPONSE AND ALERTS

Emergency Response

Dedicated emergency response button for users to request assistance from authorities

Emergency Response Types

- Fire
- Police
- Medical

Emergency Alerts²

A loud alarm or sound for:

- Break-ins, when system is armed
- Potentially unsafe levels of smoke or carbon monoxide
- Fire, carbon monoxide and burglary event

² Certain features are only available if purchased in addition to base models or packages.

SETUP AND PROGRAMMING

Cloud-Based Programming

- Program and test using AlarmNet 360 from a smartphone, tablet or a web browser
- Schedule and deliver software or firmware updates to Lyric hardware over-the-air
- Monitor system usage and activity
- Remote diagnostics and troubleshooting
- Keep a record of system test results

Lyric Lock

- Technology that allows the Gateway and sensor to be locked so they cannot be taken over

Local Programming

- Use AlarmNet 360 app to program, test and verify system operations
- Update firmware and download template into the system at the site in the absence of connection to AlarmNet 360

POWER AND OPERATING CONDITIONS

Power

- Plug-in power supply
- 110VAC mains to 9VDC with 2.5A output

Operating Conditions

32°F–122°F (0°C–50°C)

Backup Battery

- 4-hour (1100mAh) included or optional 24-hour (3700mAh)
- Rechargeable NiMH cells rated at 7.2VDC

ORDERING

LCP300-L	Lyric Gateway	SIXPIR	SiX Two-Way Wireless Motion Detector
LCP300-LC	Lyric Gateway (Canada)	SIXSMOKE	SiX Two-Way Wireless Smoke Detector (US/Latin America)
LCP300-DK	Lyric Gateway Desk Stand (included with Gateway)	SIXSMOKE-CN	SiX Two-Way Wireless Smoke Detector (Canada)
LCP500-24B	Backup Battery for Lyric Gateway (24-hour)	SIXGB	SiX Two-Way Wireless Glassbreak Detector
LCP500-4B	Backup Battery for Lyric Gateway (4-hour)	SIXFOB	SiX Two-Way Wireless Key
LKP500-EN	Lyric Keypad English	SIXSIREN	SiX Two-Way Wireless Siren
LKP500-ENC	Lyric Keypad English (Canada)	LYRIC-CDMA	Digital Cellular Communicator (Verizon®)
LKP500-DK	Lyric Keypad Desk Stand	LYRIC-3G	Digital Cellular Communicator (AT&T®)
SIXCT	SiX Two-Way Wireless Door/Window Sensor	LYRIC-3GC	Digital Cellular Communicator Canada Only (Rogers™)
SIXMINICT	SiX Two-Way Wireless Door/Window Sensor		

For more information

security.honeywellhome.com/hsc



Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492
resideo.com

The iOS app is available in iTunes. The Android app is available in the Google Play Store. iPhone, iPad and iTunes are registered trademarks of Apple Inc. All other trademarks are property of their respective owners.

L/LYCGTYD/D | 06/19

© 2019 Resideo Technologies, Inc.

This product is manufactured by Resideo and its affiliates. The Honeywell Home trademark is used under license from Honeywell International Inc. All rights reserved.



Honeywell Home