



TUXEDO TOUCH™

Commercial Color Graphic Voice Touchscreen Security Keypad and Business Controller with Integrated Wi-Fi®



Honeywell's Tuxedo Touch is a 7", high-resolution graphic touchscreen that functions as an integrated security system, building controller, camera viewer and business communications tool in one. It provides you with a cost-effective way to capture new markets by seamlessly integrating on-site security with cameras and Z-Wave® enabled thermostats, lights, locks and shades.

A built-in web server lets end-users control Tuxedo Touch anywhere within the business and view live video on up to four local cameras per screen on an iPhone®, iPad®, Android™, BlackBerry®, Internet TV or any compatible wireless mobile device.* Use either Wi-Fi or Ethernet to connect to the premises LAN.

Whether controlling the security system or other functions within a facility, the large graphic icons—which also match

the Resideo Total Connect Remote Services interface—simplify operation. Business owners can control their security system, lights, locks and thermostats, and receive event-driven alerts remotely when combined with Total Connect—a great RMR opportunity. They can also view live look-in video and receive video notifications.

The digital picture frame feature lets commercial customers showcase products in vivid detail, advertise sales and special promotions, post employee announcements, floor plans and more. They can also play videos by inserting an SD card—a great way to play commercials and draw attention to display cases. A choice of white or silver/black blend with any commercial interior. Tuxedo Touch is available in English, French Canadian and Spanish language options, with voice annunciation of alarm status (English only).

FEATURES AND BENEFITS

- 7" color widescreen display
- 800 x 480 resolution TFT display with 16 million colors
- Centralized control of security system, video cameras, Z-Wave enabled thermostats, lights, locks and more from your Tuxedo Touch
- Use either Wi-Fi or Ethernet to connect to the premises LAN
- View up to four IP cameras at once on the Tuxedo Touch display
- Built-in web server allows for local control of your Tuxedo Touch system through any Wi-Fi enabled device (smartphone, iPad, iPhone, PC, Internet TV)
- Intuitive, easy to use interface with large icons and menu driven navigation
- Fully compatible with Total Connect
- Icons match Total Connect Interface to help up-sell remote services
- Z-Wave controller built-in
- Supports up to 232 Z-Wave devices
- Most Z-Wave enabled thermostats, locks, lights and shades are compatible (see compatibility charts)
- Manage energy costs with customized scenes that can control Z-Wave enabled thermostats and lights based on system events or time and day (up to 10 scenes)
- View your local weather right on the keypad
- Customizable displays:
 - Dealer logo and company information can be customized on the homescreen
 - Digital picture frame slideshow adds around the clock enduser value
 - Video player creates digital billboard or training vehicle for your business needs
- Sunrise/Sunset — Scenes automatically update based on sunrise and sunset times
- RIS support — Z-Wave devices can activate by triggering 5800 Series zones/devices
- Voice annunciation of the type and location of alarm so endusers can act quickly in an emergency (English only)
- Three different languages can be displayed (English, French Canadian and Spanish)
- Family message center lets users record and playback messages
- Available in two colors (white and silver)
- Embedded training videos inside the keypad
 - Tuxedo Touch sales video
 - Programming Z-Wave device into Tuxedo Touch training video
 - Programming Z-Wave scenes in Tuxedo Touch
 - How to use web server for local Wi-Fi enabled device control training video
 - How to customize homescreen for dealer, digital picture frame and video viewer training video
 - How to install and program IP cameras training video

TUXEDO TOUCH Technical Specifications

COMPATIBILITY	
CONTROL PANEL	Max. No. of Tuxedo Touch Graphic Keypads
VISTA®-15P/FA148CP	2
VISTA-15PSIA/FA148CPSIA	2
VISTA-20P/FA168CPS	4
VISTA-20PSIA/FA168CPSIA	4
VISTA-21IP	4
VISTA-21iPSIA	4
VISTA-128BPE/FA1660CE	3
VISTA-128SIAE	3
VISTA-128BPT/FA1660CT	6
VISTA-128BPTSIA	6
VISTA-128FBP/FA1670C	3
VISTA-250BPE	3
VISTA-250FBP/FA1700C	3
VISTA-250BPT	6
VISTA-32FBPT	6
VISTA-128FBPT/FA1670CT	6
VISTA-250FBPT/FA1700CT	6



Zone List Screen



Slideshow Setup



Automation Screen



Camera Viewing Screen

Physical: 8.23" W x 5.59" H x 1.13" D

Wiring (Standard four-wire connection):

- Black Ground
- Red +12VDC (Aux Power)
- Green "Data in" to control panel
- Yellow "Data out" from control panel

Current Draw:

- Backlight OFF, Sound OFF - 12V, 180mA
- Backlight ON, Sound OFF - 12V, 260mA
- Backlight ON, Sound ON - 12V, 305mA

Agency Listings:

- UL 365 - Police Station Connected Burglar Alarm Units and Systems
- UL 609 - Local Burglar Alarm Units and Systems
- UL 985 - Household Fire Warning System Units
- UL 1023 - Household Burglar Alarm System Units
- UL 1610 - Central Station Burglar Alarm Units

ANSI/SIA CP-01-2010 - Control Panel Standard, Features for False Alarm Reduction

- CAN/ULC-S303-M91 - Local Burglar Alarm Units and Systems
- CAN/ULC-S304-06 - Signal Receiving Centre and Premise Burglar Alarm Control Units
- ULC-S545-02 - Residential Fire Warning System Control Units
- ULC/ORD-C1023-74 - Household Burglar Alarm System Units

ORDERING

TUXW	Color Graphic Voice Touchscreen Security Keypad and Business Controller (White)
TUXS	Color Graphic Voice Touchscreen Security Keypad and Business Controller (Silver)
TUXWIFIW	Color Graphic Voice Touchscreen Security Keypad and Business Controller with Integrated Wi-Fi (White)
TUXWIFIS	Color Graphic Voice Touchscreen Security Keypad and Business Controller with Integrated Wi-Fi (Silver)
WG-1103 (CM)/WG-3103 (CMP)	Genesis Series Cable (Standard Four-wire Connection)
WG-1133 (FT4)/WG-3103 (FT6)	Genesis Series Cable (Standard Four-wire Connection) – Canada

For more information

security.honeywellhome.com/hsc



Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492
resideo.com

*iPhone and iPad are registered trademarks of Apple® Inc. All other trademarks are properties of their respective owners.

L/TUXEDODLCD/D | 06/19
© 2019 Resideo Technologies, Inc.
This product is manufactured by Resideo and its affiliates. The Honeywell Home trademark is used under license from Honeywell International Inc. All rights reserved.

Honeywell Home